



BOW

STYLISH ENTRANCE

BOW is a stylish LED luminaire, for use at front doors and entrances. The downlighter is energy saving and has an extensive-spread distribution pattern for entrance gallery situations or deep light bundle for above entrance doors. These light bundles have been fine-tuned for the applications to avoid light pollution. The BOW has a sustainable aluminium housing and is finished with a double layer epoxy coating, which extends its service life. The wall-mounted luminaire is impact resistant (IKO8), dustproof and resistant to jets of water (IP65).

Applications



GALLERIES





PORCHES





STORAGE ROOMS









HOGRO PLUS BY LIGHTRONICS

DIMENSIONS BOW

in mm







Features

















PRODUCT SPECIFICATIONS


- Aluminium housing, double coated with epoxy for coastal areas
- · Standard colour DB703 or RAL9010
- · Screen-printed glass cover
- Dimensions (I x w x h): 260 x 134 x 130
- · Cable entry central rear
- · Safety class I
- Voltage 230/240 V, 50 Hz
- · Assembly-, installation- en maintenance friendly
- · CRI >80
- Colour temperature warm white (3000K) or neutral white (4000K)
- Expected lifespan 100.000 hours at T-ambient = 25°C (L80/F10)
- · Two different light distribution patterns, area or gallery

OPTIONS


- · Other RAL colour
- · Twilight switch
- · Comfort Light

BOW EASY LIGHT		
Lumen	LED power (W)	System power (W)
280	1,4	2,5
440	2,3	3,6
560	2,9	4,4
	Lumen 280 440	Lumen LED power (W) 280 1,4 440 2,3

BOW AREA



BOW GALLERY





Luminaires in the Easy Light version can be programmed in various luminous fluxes. They can also be optionally equipped with a twilight switch so that the fixture automatically reacts to light and dark. The sensitivity of the sensor can be adjusted by means of dipswitches.



Comfort Light has an internal motion detector and twilight switch. The automatic dimming function gradually reduces the light intensity of the luminaire (100 - 80 -50 -20% or optionally to 0%) and prevents darkness adjustment. NB: To 0% is a basement setting in which the lighting is always switched on by movement (i.e. also during the day).









